RСЛ

P56938

	-			
36pm	1 Wate	sh 2 🖸 Galta 🔅	3 Record Grand	14
	SportsCenter: Highlights of the day's sports with Linda Cohn and John Anderson			
	ESPN (3	6) 6pm (1 h	n) ee A g	
The start is	Grid	Sort	News Schedule I	
vm/nninh	Thu	6:30pm	7:00pm	I
uuyiiiyAlliy	Last	ABC News	Access Holly	
	esen	SportsCenter	Baseball	
Tonight 10/9 pm	/FOX	The Simpsons	Friends	
CBS	©CBS	CBS News	Wheel of For	J
	14	NBC News	Extra	
Some focus		Divorce Court	Power of Att	
	(B)	3rd Rock From.	Seinfeld	
A A		News Hour	Nightly Bus.	
		Home Solutio	Harry London	
	NHC	Thomas de ante		

Home Theatre[®] Series





Slimline Projection Television

Concealed Casters

REA Changing Entertainment. Again. www.rca.com

56 Projection Stereo Monitor-Receiver

- Home Theatre[™] Video System with 900 Lines of Horizontal Resolution²
- ► Digital Focus
- ► 3-Line Digital Comb Filter
- ► High Performance Scan Velocity Modulation
- ► GUIDE Plus+ GOLD¹ On-Screen Program Guide
- ► Advanced Twin Tuner[™] Picture-In-Picture
- Master Touch[®] Universal Glo-In-The-Dark Remote
- ► 10-Watt³ Stereo Amplifier
- Two Sets of Audio/Video Inputs with One S-Video Input/One Component (Y, Pr, Pb) Input/Audio Outputs

Picture

High-Performance Video System

Advanced circuitry delivers outstanding picture performance with up to 900 lines of horizontal resolution².

► Digital FOCUS

- Computer-aligned 10-bit digital circuitry provides precise and consistent picture performance from the moment the TV is turned on. Combined with Dynamic Focus, it maximizes picture brightness with sharper corner focus ensuring a beautifully detailed picture across the entire screen.
- 3-Line Digital Comb Filter Digital separation technology for color and edge detail dramatically enhances picture resolution by eliminating blurred edges between colors and reducing dot crawl, producing a new level of picture sharpness and detail.

High Performance Scan Velocity Modulation Improved SVM circuitry automatically varies the scanning speed of the picture tube's electron beam to improve sharpness and detail especially in high contrast areas.

- Adjustable Picture Control Custom picture settings are just a button press away. Adjust and store Contrast, Color, Tint, Black Level, and Sharpness settings for personal picture performance depending on your own individual tastes.
- Custom Convergence
 Adjustment

When the Earth's magnetic field interferes with the Projection TV alignment, adjustable convergence provides fine tuning for red, blue, and green Projection TV tubes. The 8-bit D/A (digital-to-analog) converter allows much finer alignment for restoring picture performance to its original setting. • Dynamic Focus

Improves corner and edge focus for an overall sharper picture.

- Adaptive Video
 Noise Reduction
 Video noise filter greatly reduces
 noisy picture interference by
 automatically adjusting to the
 incoming signal level, providing a
 cleaner and more consistent
 overall picture.
- Auto Color Balance (also called Auto Kine Bias — AKB) Beste individual picture tube que

Resets individual picture tube guns (Red, Green, Blue) to maintain consistent overall picture quality for the life of the tube.

- Wide Band Video Amplifier Delivers high resolution and clarity by extending the video frequency response. Optimizes performance from high-resolution sources such as the RCA®-DIRECTV[™] System, DVD players, and S-Video signals (S-VHS, Hi8).
- High Resolution, High Gain Screen Utilizes double lenticular and

fresnel lenses to deliver bright images over a wide viewing area.

- High Output, Liquid Cooledand-Coupled Picture Tubes High output picture tubes are liquid coupled to a precision optical system to deliver bright, clear images.
- High Transmittance Lens System
 Hybrid glass/acrylic lens system optimizes focus while providing maximum brightness.
- First Surface
 Reflective Mirror
 Provides maximum picture
 brightness and sharpness by
 reflecting more light from the
 front surface of the mirror.

Sound

- ► **10-Watt³ Stereo Amplifier** Built-in 10-watt amplifier enhances Deliver
- stereo performance. • Broadcast Stereo with dbx⁵ Noise Reduction Improves the clarity and fidelity of stereo broadcasts by restoring
 - Improves the clarity and fidelity of stereo broadcasts by restoring dynamic range and suppressing unwanted noise.
- Low-Noise Audio System Delivers a 60dB signal-to-noise ratio for spectacular quality sound.
- Sound Logic[™] Audio Leveler When turned on, eliminates the annoying "blast" of sound during commercial breaks.
- Front-Fired Speaker System Front-fired full-range frequency drivers provide excellent imaging while localizing voices at the screen.
- Second Audio Program (SAP) Decodes the second audio program available on some broadcasts.

• Dynamic BlackStretch Circuitry Extends black levels in bright

Extends black levels in bright scenes to enhance contrast and detail.

- Auto**Color**Control Automatically maintains natural tones and color fidelity from channel to channel and scene to scene.
- Adjustable Color Warmth Customer-selectable color temperature system allows for background color balance adjustment of the picture to personal preference. Setting choices are Cool, Warm, or Normal.
- Contrast/Color Tracking System Synchronizes contrast and color settings to maintain vibrant images.
- Preferred Picture Presets
 Optimize the picture by selecting
 the correct setting depending on
 the lighting conditions of the room.
 Choose between four settings for
 bright lighting, normal lighting, dim
 (soft) lighting, and a customer selectable and savable
 "personal" setting.
- Deluxe Shielded Tuner with 181-Channel Tuning Capability⁴

Special shielding dramatically reduces ghosting caused from off-air pick-up when watching cable channels. Digitally-controlled frequency synthesis tuning system "locks on" to cable and standard signals with unsurpassed accuracy.

Remote

Master Touch[®] Universal Glo-In-The-Dark Remote CRK76TA1

Ergonomic design with glo-in-thedark buttons provides complete TV operation plus control of the primary functions of virtually every brand of remote-controllable VCRs and cable boxes, and boxes, and RCA®-DIRECTV" Systems. Also controls most functions of RCA DVD Players and select functions of some brands of audio components. Frequently used buttons glow in the dark, making it easy to find the correct functions even at night.



Convenience



WHAT'S ON TV! Tonight, Tomorrow and the Next Day!



Press Here. 2 The Program

2 The Program Guide appears on your television.

> GUIDE Plus+ GOLD¹ Interactive Program Guide Find out What's On! The GUIDE Plus+ Gold¹ Program Guide is a FREE, built-in service that provides instant listings of all your TV shows at the touch of a button. View listings up to seven days in advance and enjoy the capability of One-Touch Recording to your VCR.

➤ Advanced Twin Tuner™ Picture-In-Picture

Two built-in, independent tuning systems allow both large-picture and small-picture viewing without the need for a second external video source (e.g., VCR). In addition to the standard RCA PIP feature of Swap, the Twin Tuner PIP System also provides:

-Continuous Move

Permits placement of the small picture anywhere on the screen.

-Commercial Skip-to-PIP This exclusive RCA feature allows the main picture to move to the PIP

window simultaneously with the activation of an on-screen countdown timer. The viewer can then monitor the original program while browsing through other channels during commercial breaks.

Commercial Skip

Countdown timer returns TV to original channel, so other channels can be browsed during program breaks.

Auto Tune

After initial setup, just pressing one component button on the TV's remote (either VCR, RCA®-DIRECTV" System, cable, or DVD) turns on both the TV and the component and also automatically tunes the TV to the correct viewing channel. Just one press!

• Picture Memory for

Video Inputs Custom picture settings are activated whenever direct video inputs are selected. Allows tailored picture performance with each video source.

- Picture Reset Instantly returns picture to factory settings for Color, Tint, Contrast, Brightness, and Sharpness.
- Advanced Auto
 Channel Search

Auto Cable/Air Switch sets tuner to cable or "off-air" frequencies during initial setup. Then system automatically scans for and locks active channels into channel memory.

- On-Screen Menu System
 On-screen displays make it easy
 to adjust most picture, sound, and
 convenience features from either the
 remote control or the TV front panel
 buttons.
- Interactive Setup Menu Convenient on-screen menu system automatically steps user through the initial setup procedures.
- **Trilingual On-Screen Display** Allows the on-screen menu system to be displayed in one of three languages (English, French, or Spanish).

On-Screen Time and Channel Display Displays time and channel number at

Displays time and channel number a the press of a button.

2 ways to find your programs







 Programmable Timer System Convenient scheduling system can be used in a variety of ways:
 Sleep Timer

Automatically turns off the TV after

a preset time period — for those times when you drift off to sleep in front of the television. -Alarm Timer

Wake up to your favorite morning show or turn on your television automatically to catch your favorite program.

-Scheduling Timer Since the alarm setting remains in the TV memory indefinitely, the TV can be scheduled to turn on at the same time every day.

Channel Labeling

Assign on-screen characters to easily identify channels (e.g., NBC, HBO, ESPN, VH-1).

- Front Panel Lockout Completely disables front panel controls to prevent toddlers from altering settings.
- V-Chip Parental Control
 Puts control back into the hands of
 the viewer by blocking unwanted
 television broadcasts with U.S.
 Government required circuitry. Blocks
 three types of programs: regular
 television programs, broadcast
 movies and unrated programs.

The Grid Guide

Using your remote, easily scroll through current or future TV listings to see what's on. As each program is highlighted, an informative summary appears in the Program Info area.

The Sort Guide

Find your favorite sports, movies, or kids' programs, for up to seven days in advance, instantly with the Sort Guide.

And The Benefit of One-Touch Record*

Even if your VCR is flashing 12:00, the GUIDE Plus+ GOLD' Program Guide can record your favorite shows. Simply use your remote to highlight the program you want to record, set it to record and the GUIDE Plus+ GOLD' Program Guide does the rest! You can even set shows to record daily and weekly! *compatible with most VCRs

MSNBC News Guide

Check out up-to-date national and world news stories from MSNBC in the News Guide. Comprehensive coverage includes business, sports, and entertainment news.

> Program rating information is sent by the broadcaster continuously during the program. The television will match program rating to user preference and block the entire program (when program is aired with the encoded signal). User preference is secured using a four-digit password.

• Non-Volatile Memory In case of most power outages, the picture adjustments and channel selections are stored in electronic memory.

• Caption Vision C Closed Caption Capability⁶ Assists the hearing impaired, helps children learn to read, and aids in the teaching of English as a second language. Built-in Closed Caption Decoder displays the audio portion of a program as text on the TV screen (when program is aired with the encoded signal).

Slim Cabinet Design Unique optics system utilizes radius phosphor tubes to shorten the interior light path resulting in enhanced picture quality with a super-slim cabinet profile with reduced depth.

Connections

Audio/Video Input Jacks with S-Video Inputs

Color-coded monitor panel provides direct audio and video connections for optimum performance and system flexibility. Includes two audio/video inputs, one S-Video input, plus switchable audio outputs for fixed and variable level control.

G-LINK¹ Connector

The G-LINK' connector allows the GUIDE Plus+ GOLD' Program Guide System to work with your VCR (enabling one-touch record) and/or cable box (ability to tune directly to a station when the program guide is on your TV screen).

INPUT 1

VIDEO

• Back Panel

• One Pair of Switchable (Variable/Fixed) Audio Outputs

Connect TV to an external audio source with speakers (AV receiver, subwoofer, power amplifier) to create a true home theater setup. Switchable outputs offer maximum flexibility for connecting various types of external audio components.

S-Video/Component Inputs with Auto Detection


One direct Y/C input and one set of component (Y, Pr, Pb) inputs connect TV to compatible sources (e.g., DVD players, RCA®-DIRECTV[™] Systems, S-VHS VCRs/Hi8 VCRs/camcorders, or Internet set-top devices) for high-resolution playback. Automatic switching to either input upon detection of the signal so there's no setup necessary.

Limited Warranty

- One year for labor charges.

Plus

- One year for parts.
- Two years for picture tube.
 See RCA dealer or visit www.rca.com for
- complete details.



INPUT 2

6

AUDIC

0

 \odot

ଚ

Specifications				
	P56938			
Screen Size (diagonal)	52"			
Finish	Metallic Diamond			
Cabinet Dimensions	61¼" H, 51½" W, 26" D			
Approx. Shipping Weight	000 Lbs.			
Concealed Casters	Yes			
Lines of Horizontal Resolution	900 ²			
Audio Power	10 Watts			

- 1 GUIDE Plus+ GOLD and G-LINK are trademarks of Gemstar-TV Guide International, Inc.
- 2 Lines per picture width, 675 lines based on EIA measurement criteria.
- 3 10 watts = 5 watts per channel, RMS rating into 8 ohms 50 Hz-20,000 Hz, ± 3dB with less than 1% THD.
- 4 Check your cable company's compatibility requirements.
- 5 dbx is a registered trademark of Carillon Electronics Corporation
- 6 This television receiver provides display of television closed captioning in accordance with §15.119 of the FCC rules. This television receiver does not support color attributes of television closed captioning.





©2001 Thomson multimedia Inc.

Form S-P56938-R1 Trademark(s) ® Registered Marca(s) Registrada(s) Photos and features subject to change without notice. Illustration of product finish may vary from actual color. Screen sizes measured diagonally. Printed in the U.S.A. 3/01

PC15892 GAC38656